

PSM® 900 In-Ear Personal Monitoring System

The PSM 900 In-Ear Personal Monitoring System from Shure offers a clear and accurate audio quality and robust RF performance. Innovative features allowing for ease of use and quick setup make it the ideal solution for most demanding professional applications. The patent-pending CueMode allows the sound engineer to monitor different stage mixes with the touch of a button whereas precision front-end RF filtering significantly reduces dropouts from RF interference.



APPLICATIONS

Touring Sound

House Of Worship

Broadcast

Theater

PRODUCT HIGHLIGHTS

Full-Metal Bodypack Receiver

Rechargeability

RF-Mute

Up to 40 MHz Tuning Bandwidth

Up to 20 Compatible Frequencies per Band Version

Group Scan

CueMode (patent pending)

Active RF Gain Control

System Specifications

RF Carrier Range	470 – 952 MHz (regionally dependent)
Compatible Frequencies	20 per band
Tuning Bandwidth	36 MHz – 40 MHz (regionally dependent)
Operating Range (environment dependent)	90 m
Audio Frequency Response	35 Hz – 15 kHz
Stereo Separation	60 dB
Signal-To-Noise Ratio (A-Weighted)	90 dB (typical)
Total Harmonic Distortion (ref. ±34 kHz deviation @ 1 kHz)	<0.5% (typical)
Comping	Patented Shure Audio Reference Comping
Spurious Rejection (ref. 12 dB SINAD)	>80 dB (typical)
Frequency Stability	±2.5 ppm
MPX Pilot Tone	19 kHz (±0.3 kHz)
Modulation	FM, MPX Stereo (±34 kHz deviation, nominal)
Operating Temperature	-18°C – +57°C

Furnished Accessories

P9R Antenna	
UA700	470 – 542 MHz
UA720	596 – 692 MHz
UA730	692 – 830 MHz
UA740	830 – 952 MHz
P9T Antenna	
UA820G	470 – 530 MHz
UA820G7	500 – 560 MHz
UA820H4	518 – 578 MHz
UA820J	578 – 638 MHz
UA820L3	638 – 698 MHz
UA820B	690 – 746 MHz
UA820Q	740 – 814 MHz
UA820A	774 – 865 MHz
UA820X	900 – 952 MHz
95A9023	Front Mount Antenna Cable
95A2313	Zipper Bag
53A8612	Rackmount Bracket, Long
53A8611	Rackmount Bracket, Short
53B8443	Link Bar
90AR8100	Hardware Kit (Rackmounting Screws)
90B8977	Bumper Kit
Energy Efficient Switching Power Supply	
PS41US	USA
PS41BR	Brazil
PS41AR	Argentina
PS41E	Europe
PS41UK	United Kingdom
PS41AZ	Australia/New Zealand
PS41CHN	China
PS41TW	Taiwan
PS41J	Japan


Frequency Range

Band	Range	RF Output Power***
G6	470 – 506 MHz	10 / 50 / 100 mW
G6E	470 – 506 MHz	10 / 50 mW
G7	506 – 542 MHz	10 / 50 / 100 mW
G7E	506 – 542 MHz	10 / 50 mW
K1	596 – 632 MHz	10 / 50 / 100 mW
K1E	596 – 632 MHz	10 / 50 mW
L6	656 – 692 MHz	10 / 50 / 100 mW
L6E	656 – 692 MHz	10 / 50 mW
P7	702 – 742 MHz	10 / 50 mW
Q15	750 – 790 MHz	10 / 50 mW
Q20	750 – 787 MHz	10 / 50 mW
R20	794 – 806 MHz	10 mW
R21	794 – 806 MHz	10 / 50 mW
R22	790 – 830 MHz	10 / 50 mW
A24	779 – 806 MHz	10 mW
X2	925 – 932 MHz	10 mW
X1	944 – 952 MHz	10 / 50 / 100 mW

***Regionally Dependent

Antennas, Combiners and Accessories

PA821SWB	8-to-1 antenna combiner for better RF performance
PA421SWB	4-to-1 antenna combiner with power distribution to 4 transmitters (better RF performance and eliminates need for external power supply)
PA805SWB	Passive Directional Antenna
HA-8089	Helical Antenna (470 – 900 MHz)
HA-8241	Helical Antenna (944 – 952 MHz)
PA860SWB	Passive Omnidirectional Antenna
P4M	4-Channel Personal Monitor Mixer
UA802	Coaxial Cable, BNC, RG58C/U type, 50 Ω, 0.6 m length
UA806	Coaxial Cable, BNC, RG58C/U type, 50 Ω, 2 m length
UA825	Coaxial Cable, BNC, RG8X/U type, 50 Ω, 7.5 m length
UA850	Coaxial Cable, BNC, RG8X/U type, 50 Ω, 15 m length
UA8100	Coaxial Cable, BNC, RG8X/U type, 50 Ω, 30 m length
SBC800	8-Up Battery Charger
SB900	Rechargeable Battery
SB900-8	8-Pack Rechargeable Batteries



SB900 Rechargeable Battery

The P9RA bodypack is compatible with the SB900 lithium-ion rechargeable battery, which provides extended usage time of up to 10 hours and precise tracking of remaining life and charge cycle details.


SBC800 Recharging Station

This compact unit charges up to 8 SB900 batteries to full capacity within 2 hours, with status LEDs to indicate power levels. SB900 batteries fit securely in the charger for easy, efficient storage and transport.

SHURE[®]
LEGENDARY
PERFORMANCE™

Component Specifications



P9RA Wireless Bodypack Receiver



The P9RA is a low-profile bodypack receiver for use with the PSM 900 Wireless Personal Monitoring System. It offers premium features like Group Scan and Automatic RF Gain Control for unparalleled signal stability and channel availability, all packed in the slimmest form factor available. Patent-pending CueMode allows monitoring of different stage mixes and storing of up to 20 separate channels from one bodypack for quick and easy mix reference. Optional advanced rechargeability eliminates the need for disposable batteries and provides extended usage times with reliable battery life.

Front-End RF Filtering	-3 dB point 30.5 MHz from center frequency
Active RF Gain Control	31 dB (adjusts RF sensitivity to provide more RF dynamic range)
RF Sensitivity (20 dB SINAD)	2.2 μ V
Squelch Threshold (\pm3 dB SINAD)	22 dB SINAD
Adjacent Channel Rejection	>70 dB
Intermodulation Attenuation	>50 dB
Blocking	>80 dB
Image Rejection	>90 dB
Audio Output Power (1kHz @ <1% distortion, peak power, @32 Ω)	100 mW
Minimum Load Impedance	9.5 Ω
High Boost	Selectable: +2 dB / +4 dB @ 10 kHz
Volume Limiter	Selectable: 3 - 9 (Reduces maximum output level. Selected value corresponds to volume knob increment)
Battery Life	4 - 6 hours (continuous use with Alkaline batteries)
Net Weight	200 g with batteries
Dimensions	83 mm x 65 mm x 22 mm

P9T Wireless Transmitter



The P9T is a half-rack wireless transmitter used in conjunction with the P9R Bodypack receiver as part of the PSM 900 In-Ear Personal Monitoring System. It offers state-of-art technology like CueMode (patent pending), Scan and Sync, and RF mute switch for easy setup and operation. Connections include balanced 1/4" and XLR, loop out, and headphone out. Includes rack-mounting kit, front or back mountable antennas, and power supply.

RF Output Power	Selectable: 10 / 50 / 100 mW (regionally dependent)
RF Output Impedance	50 Ω (typical)
Net Weight	850 g
Dimensions	197 mm x 166 mm x 42 mm
Power Requirement (RF on, 100 mW power mode, no audio)	15 Vdc at 415 mA, supplied by external power supply
Audio Input	
Connector Type	Combination XLR and 6.35 mm (1/4") TRS
Polarity	XLR: Non-inverting (pin 2 positive with respect to pin 3) 6.35 mm (1/4") TRS: Tip positive with respect to ring
Configuration	Electronically balanced
Impedance	70.2 k Ω (actual)
Nominal Input Level	Switchable: +4 dBu / -10 dBV
Maximum Input Level	+4 dBu: +29.2 dBu -10 dBV: +12.2 dBu
Pin Assignments	XLR: 1 = ground, 2 = hot, 3 = cold 6.35 mm (1/4") TRS: Tip=hot, Ring=cold, Sleeve=ground
Phantom Power Protection	Up to 60 V DC
Audio Output	
Connector Type	6.35 mm (1/4") TRS
Configuration	Electronically balanced
Impedance	Connected directly to inputs

SHURE[®]
LEGENDARY
PERFORMANCE™

Europe, Middle East, Africa:
Shure Europe GmbH
Jakob-Dieffenbacher-Str. 12
75031 Eppingen, Germany

Phone: 49-7262-92490
Fax: 49-7262-9249114
Email: info@shure.de

United Kingdom, Ireland:
Shure Distribution UK
Unit 2 The I O Centre
Lea Road
Waltham Abbey EN9 1AS
United Kingdom

Phone: +44 (0) 1992 703058
Fax: +44 (0) 1992 703057
Email: info@shuredistribution.co.uk
www.shure.co.uk